

V200 Input Monitor Interface

Alarm Input Processing for up to 16 Zones • 70200



ACCESS opportunity.

The HID VertX™ products provide a complete and fully featured hardware/firmware infrastructure for access control software host systems. The V200 input monitor interface connects up to 16 supervised input circuits. Each input point monitors and reports normal, off-normal, and alarm states. The V200 features on-board flash memory, allowing program updates to be downloaded through the network. The V200 connects to the VI000 via a high speed RS-485 network. The VI000, in turn, communicates with the system host via industry standard TCP/IP protocol, over 10/100 Mbps Ethernet, or the Internet. This architecture minimizes the impact on corporate LANs, by using only one TCP/IP address for every 32 interfaces, and by handling low-level transactions on the RS-485 network.

Features

- ▶ Reports supervised or un-supervised alarm circuits
- ▶ Off-normal condition programmable for each input point (NO or NC alarm devices may be used)
- ▶ Connects to the VI000 via RS-485
- ▶ Receives and processes real time commands from the VI000
- ▶ Reports all activity to the VI000
- ▶ Allows complex input/output linking when used with the VI000 and V300 Output Control Interface
- ▶ Attractive polycarbonate enclosure protects components from damage
- ▶ All connections and indicators are fully identified by silk-screened nomenclature on the cover
- ▶ UL 294 and UL 1076 recognized components

Mounting Mount to any wall surface, using four screws. For UL compliance, one or more interfaces can be mounted inside a locking customer-supplied NEMA-4 rated enclosure with:

- DC supply with battery back-up
- Enclosure tamper switch
- All connections made through conduit

The unit should be installed indoors, inside a secure area, such as in an IT or telecommunications room, utility closet, or on a wall above a suspended ceiling.

Visual Indicators Communications LED flashes green for “transmit to host” and red for “receive from host.” Power LED indicates that sufficient DC voltage is being provided to the unit.

Easily Interfaced

- Quick-disconnect screw terminal connectors
- Rotary address switch (0-15)
- Inputs for:
 - 16 input circuits
 - AC Fail Monitor*
 - Battery Fail Monitor*
 - Enclosure Tamper*

*Can be configured as a general purpose input

Non-latching relay outputs (rated 2 A @ 30 VDC):

- 2 auxiliary devices: alarm host offline (comms down), or general purpose

Local Processing

- Basic input/output linking using inputs 1 and 2, and auxiliary outputs 1 and 2

Warranty Warranted against defects in materials and workmanship for 18 months. (See complete warranty policy for details.)

Part Numbers Base Part Number: 70200

Dimensions
5.8” W x 4.825” H x 1.275” D
(147.32 mm x 122.55 mm x 32.38 mm)

Weight: 12.4 oz (.35 kg)

Enclosure Material: UL94 Polycarbonate

Power Supply Requirements
50 mA @ 9-18VDC
Recommended: Supervised linear power supply with battery back-up, input surge protection, and AC fail and battery low contact outputs.
Separate supervised DC supply with battery back-up recommended for relay activated devices.

Operating Environment
Indoors, or customer-supplied NEMA-4 rated enclosure

Temperature
32° to 122° F (0° to 50° C)

Humidity
5% to 95% relative, non-condensing


Communications Ports
RS-485 - two wire.

Input Circuit Supervision
Configurable for EO resistor values of 1K through 10K. Can also be configured for use as unsupervised circuits.

Certifications
UL 294 and UL 1076 Recognized Component for the US, CSA 205 for Canada, FCC Class A Verificatio, EMC for Canada, EU (CE Mark), Australia (C-Tick Mark), New Zealand, Japan EN 50130-4 Access Control Systems Immunity for the EU (CE Mark)

Cable Distance
RS-485 – 4000 feet (1220 m) to host, using Belden 3105A, 22AWG twisted pair, shielded 100Ω cable
Input Circuits – 500 feet (150 m), two-conductor, shielded, using ALPHA 1292C (22AWG) or Alpha 2421C (18AWG)
Output Circuits – 500 feet (150 m), 2-conductor, using ALPHA 1172C (22AWG) or Alpha 1897C (18AWG)
Minimum wire gauge depends on cable length and current requirements.

© 2007 HID Global. All rights reserved. HID, the HID logo, and VertX are trademarks or registered trademarks of HID Global in the U.S. and/or other countries. All other trademarks, service marks, and product or service names are trademarks or registered trademarks of their respective owners. Rev. 3/2007

 For best results, please print on recycled paper.

MKT-V200_DS_EN



ACCESS experience.

hidcorp.com

HID Global Offices:

Corporate North America
9292 Jeronimo Road
Irvine, CA 92618-1905
U.S.A.
Phone: (800) 237-7769
Phone: (949) 598-1600
Fax: (949) 598-1690

Asia Pacific
19/F 625 King's Road
North Point
Island East
Hong Kong
Phone: +852 3160-9800
Fax: +852 3160-4809

Latin America
Circunvalacion Ote. #201 B
Despacho 2
Col. Jardines del Moral
Leon 37160, Gto.
Mexico
Phone: +52 477 779 1492
Fax: +52 477 779 1493

Europe, Middle East & Africa
Homefield Road
Haverhill, Suffolk
CB9 8QP
England
Phone: +44 (0) 1440 714 850
Fax: +44 (0) 1440 714 840